



Zero Resistance Ammeter

FEATURES

- Over/Under range LEDs
- 500mA Range
- 3.5 digit Meter
- Buffered Outputs

DESCRIPTION

Many users like the single function Zero Resistance Ammeter. It is very simple to use and ideal for testing simple galvanic couples. Having a meter on the front makes it easy to monitor the Galvanic Current visually every few hours. Ideal for use in a teaching establishment, it gives the student a good feel for corrosion.

APPLICATIONS

- Teaching

Technical Specifications	
Dimensions	30.5 x 11.8 x 27.3 cm
Weight	3.8 Kg
Power Supply	110 (on request) / 230 VAC 50-60Hz
Current Output	500 mA
Connectors	Banana sockets.
Ranges	7 (10, 100, 1K, 10K 100K, 1M, 10M)
Buffered Outputs	2 mA, ± 14 V
Meter	3½ digit, u, m, A and V
Operational Temperature	-5 °C to 72 °C

ACM Instruments

125 Station Road, Cark, Grange-over-Sands, Cumbria, LA11 7NY, United Kingdom.

r.p.gill@acminstruments.com

www.potentiostat.com

Telephone: +44 (0)15395 59185

Fax: +44 (0)15395 58562